

HIGHPASS FILTERS

Cutoff Frequency (MHz)	Part Number	Insertion Loss (dB)	VSWR (∞:1)	Rejection (dB) (1)	From (MHz) (1)	To (MHz) (1)	Rejection (dB) (2)	From (MHz) (2)	To (MHz) (2)	Rejection (dB) (3)	From (MHz) (3)	To (MHz) (3)	Size (L) (inches)	Size (W) (inches)	Size (D) (inches)
1	THP-L-11027														
9	THP-L-11500														
20	THP-L-12341	1		55	13	13							2.38	1	1
20	THP-L-12532	0.5		60	0	5									
30	THP30-4ST1	2.2	1.7	30	20										
30.14	THP-C-15392	1.5	2	55	0	22.6									
31	THP-L-12762			3	28	28							1.68	0.4	0.4
43.3	THP-L-14067			45	36.7	36.7							1.45	0.6	0.42
50	THP-L-15221	1	1.5	25	35	35									
60	THP-L-11248														
86.6	THP-L-14066			45	73.4	73.4							1.45	0.6	0.42
100	THP-L-15313	0.8	1.7	70	75	75									
100	THP-L-07121														
120	THP-L-15222	1	1.5	17	100	100									
120	THP-L-14597	1	1.5	40	0	90									
136	THP-L-10555														
140	THP-L-11249														
140	THP-L-11249														
186	THP-L-15091	1	1.2	20	155	155	50	130	130						
200	THP-L-06250	1		30	2.4007	2.4007	30	151.4	151.4						
200	THP-L-12828	1		50	0	250							1.68	0.4	0.4
216	THP-L-10556														
250	THP-L-15364	1	2	9	224	224	15	200	200	35	110	110			
276	THP-L-11813			50	5	252									
300	THP-L-11206														
300	THP-L-12534	0.6		60	0	75							1	0.5	0.52
330	THP-L-10557														
350	THP-L-12258	1													
390	THP-L-10635	1		41	278	278	41	279	279				1.5	0.5	0.4
420	TPF-L-06469												1.9	0.4	0.4
450	THP-L-10459														
450	THP-L-14093	1		52	271	271							2.5	0.6	0.5
500	THP-L-15092	1	1.2	20	415	415	50	350	350						
500	THP-L-10464	1		40	200	2000							1.5	0.4	0.4
600	THP-L-06558	2		70	450	450							1.9	0.4	0.4
720	THP-L-10662	1.5		40	370	370							2.23	0.5	0.4
800	THP-L-06694	1		70	450	450							1.8	0.4	0.4
830	THP-L-12834	2.5		25	780	780							1.45	0.5	0.4
850	THP-L-14315			30	0	750							1.5	0.44	0.31

